



KNX radio button 4gang quicklink BERKER S.1/B.3/B.7, polar white glossy

85648189

Radio transmission/reception frequency	868,3 MHz
Radio protocol	KNX Radio
Transmitter duty cycle	1 %
Receiver category	2
Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Radio transmission power	< 10 mW
Radio transmission range (free field)	max. 100 m
Radio transmission range (building)	max. 30 m
Energy-saving	low intrinsic energy requirement
quicklink functions	quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory
ETS additional functions	ETS additional functions: +6 scenes, 1 button control up/down, operating mode on/off, dimming value, brightness display, push-button, status display, forced control
LED	with configuration and function LEDs ; LED application module/insert compatibility display
Button / push-button	with configuration and function button
Operation	operating areas configurable as one or two-area operation
Brightness	switch-on brightness level for each operating area on configuration with dimmer insert, power failure proof, storable
Protection	with dismantling protection
Programming	toolless quicklink configuration using buttons and LED display