

MDT Power Supply, MDRC

Version		
STV-160.01	Power Supply	4SU MDRC, 160mA
STV-320.01	Power Supply	4SU MDRC, 320mA
STV-640.02	Power Supply	4SU MDRC, 640mA

The MDT KNX Power Supply with integrated choke produces the stabilized KNX system voltage (30VDC) to supply the connected KNX/EIB components. The operating status is indicated via 3 LED:

- Red LED: Reset of the KNX/EIB bus
- Green LED: Normal operation, no faults
- Yellow LED: KNX/EIB bus overload

Once the fault has been rectified, the Power Supply restarts itself.

Additionally the Power Supply STV-640.02 offers a choke free output.

All devices are 100% overload safe.

The MDT KNX Power Supply is a modular installation device for fixed installation in dry rooms. It fits on DIN 35mm rails in power distribution boards or closed compact boxes.

STV-160.01



STV-320.01



STV-640.02



- Production in Germany, certified according to ISO 9001
- KNX power supply with integrated choke
- Mains voltage 230VAC
- **Short-circuit-proof**
- **Overload safe**
- LED indicator for bus reset, normal operation and bus overload
- 3 years warranty

Technical Data	STV-160.01	STV-320.01	STV-640.02
Voltage			
Supply voltage	230VAC/50Hz	230VAC/50Hz	230VAC/50Hz
KNX output voltage	30VDC	30VDC	30VDC
Choke free output voltage	--	--	30VDC
Current			
Nominal current	160mA	320mA	640mA
Continuous current	240mA	480mA	960mA
Peak current	320mA	640mA	1200mA
Max. total current of both outputs	--	--	1000mA
Efficiency at nominal load typ.*	> 83%	> 85%	> 88%
Power loss no load operation typ.	< 0,8W	< 0,8W	< 0,9W
Permitted wire gauge			
Screw terminal	0,5 - 4,0mm ² solid core 0,5 - 2,5mm ² finely stranded	0,5 - 4,0mm ² solid core 0,5 - 2,5mm ² finely stranded	0,5 - 4,0mm ² solid core 0,5 - 2,5mm ² finely stranded
KNX busconnection terminal	0,8mm Ø, solid core	0,8mm Ø, solid core	0,8mm Ø, solid core
Operation temperature range	0 to + 45°C	0 to + 45°C	0 to + 45°C
Enclosure	IP 20	IP 20	IP 20
Dimensions MDRC (Space Units)	4SU	4SU	4SU

* Efficiency before choke

Exemplary circuit diagram STV-320.01

